

# CINDE

## POWERMANAGER

### PowerManager Range

PM5 (5 volts)

PM9 (9 volts)

PM12 (12 volts)

PM24 (24 volts)



The Cinde PowerManagers are an ideal problem-solving product that crosses over into all AV markets and applications. Anyone with experience working behind an equipment rack has been forced to deal with a proliferation of external power supplies that lead to equipment rack clutter, outlet space issues (never enough), and no power supply redundancy. PowerManager replaces multiple external DC power supplies with one central, AC to DC converter, eliminating clutter while offering power redundancy.

Each PowerManager provides 6 phoenix style connectors for direct wiring to the DC device. PowerManager-5 for 5VDC, PowerManager-9 for 9VDC PowerManager-12 for 12VDC & PowerManager-24 for 24VDC applications, providing the flexibility needed for each project.

The 1/2 rack width, 1RU chassis fits into any professional installation and two units can be coupled together to save even more space in the rack. A front panel LED provides visual indication that maximum power capacity is approaching.

# DATASHEET - PowerManager

## Features

- 6 Output connectors
- Power ON LED on front
- Overload indicator with front mounted LED
- 1u (rack unit) high, half rack unit width
- 2 units can be installed together for full width mounting, rack ears are required and can be ordered separately
- Fan forced cooling
- 2 year warranty



### Specifications 5 Volt Unit (PM5)

Power Output 60 watts @ 5volts  
Total Current 12amps  
I/P Voltage 240VAC  
C tick approved

Operates from zero to full load

### Specifications 9 Volt Unit (PM9)

Power Output 100 watts @ 9volts  
Total Current 11amps  
I/P Voltage 240VAC  
C tick approved

Operates from zero to full load

### Specifications 12Volt Unit (PM12)

Power Output 100 watts @ 12volts  
Total Current 8.5amps  
I/P Voltage 240VAC  
C tick approved

Operates from zero to full load

### Specifications 24Volt Unit (PM24)

Power Output 150 watts @ 24volts  
Total Current 6.5amps  
I/P Voltage 240VAC  
C tick approved

Operates from zero to full load



**Manufactured & Distributed by**  
**Impax Communications P/L**  
Level 1, 187 Johnston St Fitzroy Vic 3065  
Phone: (03) 9329 9955 Fax: (03) 8669 4399